

Hardware Unit Test Report

DCDC Power measurement

Hardware version	FW version	Sample No.	eMMC Flash P/N
V015	None	S/N: 2152001215-01S1	None

1. PCBA Setup

PCBA only SMT on some parts of power IC, so the test is achieved by vendor. Some detail will be ignored.


Measure circuits:

There are 4 power circuits need to measure and check the power efficiency can reach 80% and 85%.

The power circuits and DCDC consumption with full load notes are as below:


1. VDDCPU

VDDCPU is about **0.92V/368.5mA** usage in full load condition with playing 4Kp60 video from YouTube.




2. VDD_EE

VDD_EE is about **0.82V/688.8mA** usage in full load condition with playing 4Kp60 video from YouTube.




3. P1V2

P1V2 is about **1.2V/553.4mA** usage in full load condition with playing 4Kp60 video from YouTube.



4. P3V3

P3V3 is about **3.3V/280.5mA** usage in full load condition with playing 4Kp60 video from YouTube.



Criteria:

1. VDDCPU

Spec	Test result
Rail VDDCPU: Vout=0.92V, +/-100mV Power efficiency=80% Power loss=20%	Pass

2. VDD_EE

Spec	Test result
Rail VDD_EE: Vout=0.82V, +/-100mV Power efficiency=80% Power loss=20%	Pass

3. P1V2

Spec	Test result
Rail P1V2: Vout=1.2V, +/-100mV Power efficiency=85% Power loss=15%	Pass

4. P3V3

Spec	Test result
Rail P3V3: Vout=3.3V, +/-100mV Power efficiency=90% Power loss=10%	Pass


2. Test Results

1. VDDCPU

1. Efficiency


Vin	Iin	Vout	Iout	Eff	Loss	Pass/Fail
5.127	0.0011	0.882	0	0.00%	0.00%	--
5.122	0.0212	0.8765	0.0987	79.67%	20.33%	Fail
5.117	0.0414	0.874	0.1987	81.98%	18.02%	Pass
5.112	0.061	0.8697	0.2987	83.31%	16.69%	Pass
5.107	0.0802	0.8674	0.3993	84.56%	15.44%	Pass
5.102	0.1004	0.8653	0.4993	84.34%	15.66%	Pass
5.118	0.121	0.8654	0.5987	83.66%	16.34%	Pass
5.11	0.1426	0.8636	0.6987	82.81%	17.19%	Pass
5.075	0.2129	0.8549	1	79.12%	20.88%	Fail
5.043	0.3477	0.8459	1.5006	72.39%	27.61%	Fail
5.004	0.5079	0.8357	2.0012	65.80%	34.20%	Fail

Efficiency Chart:




2. Ripple

0A:



2A:




3. Load transient

0.5A→2A



2A→0.5A




0.5A $\leftarrow\rightarrow$ 2A




4. bode plot

0.3A:



2A:




2. VDD_EE

1. Efficiency:

Vin	Iin	Vout	Iout	Eff	Loss	Pass/Fail
5.1447	0.0011	0.825	0	0.00%	0.00%	--
5.1402	0.0199	0.821	0.0987	79.22%	20.78%	Fail
5.1357	0.039	0.8193	0.1987	81.28%	18.72%	Pass
5.1313	0.0577	0.8147	0.2987	82.19%	17.81%	Pass
5.1271	0.0758	0.8113	0.3993	83.36%	16.64%	Pass
5.116	0.0945	0.8094	0.4987	83.49%	16.51%	Pass
5.117	0.1141	0.8075	0.5987	82.80%	17.20%	Pass
5.113	0.1346	0.8057	0.6987	81.80%	18.20%	Pass
5.0985	0.2018	0.7894	1	76.72%	23.28%	Fail
5.0696	0.3306	0.7883	1.5006	70.58%	29.42%	Fail
5.0354	0.4858	0.7788	2.0012	63.71%	36.29%	Fail

Efficiency Chart:




2. Ripple

0A:




2A:



3. Load transient

0.5A→2A:



BFX-AT100 V015 Hardware unit test report

2A→0.5A:




0.5A↔2A:




BFX-AT100 V015 Hardware unit test report

4. bode plot

0.3A:



2A:




3. P1V2

1. Efficiency

Vin	Iin	Vout	Iout	Eff	Loss	Pass/Fail
5.1637	0.0012	1.2001	0	0.00%	0.00%	--
5.1584	0.0277	1.1986	0.0987	82.79%	17.21%	Fail
5.1524	0.0543	1.1961	0.1987	84.95%	15.05%	Pass
5.1471	0.0803	1.193	0.2987	86.22%	13.78%	Pass
5.1418	0.1059	1.1908	0.3993	87.32%	12.68%	Pass
5.1364	0.1324	1.1887	0.4987	87.17%	12.83%	Pass
5.1068	0.1596	1.1783	0.5987	86.55%	13.45%	Pass
5.103	0.1876	1.1878	0.6987	86.69%	13.31%	Pass
5.1068	0.2762	1.1783	1	83.54%	16.46%	Fail
5.0727	0.4426	1.1683	1.5006	78.09%	21.91%	Fail
5.0328	0.637	1.1589	2.0012	72.34%	27.66%	Fail


Efficiency Chart:




BFX-AT100 V015 Hardware unit test report

2. Ripple

0A:



2A:




3. Load transient

0.5A→2A:



2A→0.5A:




BFX-AT100 V015 Hardware unit test report

0.5A↔2A:




4. bode plot

0.3A:



2A:




4. P3V3

1. Efficiency


Vin	Iin	Vout	Iout	Eff	Loss	Pass/Fail
5.1648	0.001	3.326	0	0.00%	0.00%	--
5.1505	0.07	3.327	0.0987	91.08%	8.92%	Pass
5.1348	0.1385	3.3178	0.1987	92.70%	7.30%	Pass
5.1206	0.2064	3.3132	0.2987	93.64%	6.36%	Pass
5.1047	0.2742	3.3116	0.3993	94.47%	5.53%	Pass
5.0891	0.3436	3.31	0.4987	94.40%	5.60%	Pass
5.062	0.4153	3.3128	0.5987	94.35%	5.65%	Pass
5.05	0.4851	3.312	0.6987	94.46%	5.54%	Pass
5.0057	0.7017	3.3026	1	94.02%	5.98%	Pass
4.9136	1.1173	3.2963	1.5006	90.10%	9.90%	Pass
4.8255	1.5709	3.2912	2.006	87.10%	12.90%	Fail

Efficiency Chart:




2. Ripple

0A:




BFX-AT100 V015 Hardware unit test report

2A:




3. Load transient

0.5A→2A:




BFX-AT100 V015 Hardware unit test report

2A→0.5A:




0.5A↔2A:



4. bode plot

0.3A:



2A:

