

HON HAI Precision IND.CO.,LTD.

5F-1,5,Hsin-An Road,
Hsinchu Science-Based Industrial Park,
Taiwan, R.O.C.

Tel: 886-3-5784975 Fax: 886-3-5783038

Reliability Test Report for BFX-AT100

Prepared by Jackson Huang
Test Engineer, HWQA Engineering Dept.

Checked by Kenji Chen
Supervisor, HWQA Engineering Dept.

Approved by Jy Deng
Manager, HWQA Engineering Dept.

Revision Change History

Revision	Description of Change	Date
1.0	Initial Release	12/14/2021

HON HAI PRECISION IND. CO., LTD.

Notice:

All rights reserved. Except for distribution within company that authorized by Foxconn, passing on and copying of this document, use and communication of its contents with the third party is not permitted without written authorization from HON HAI PRECISION IND. CO., LTD.

Table of Contents

Table of Contents 1

Purpose: 2

Scope: 2

Second source: 2

The summary of test items: 3

Panel Drawing: 4

Test setup and function test: 4

1. Cold Start Test 5

2. Hot Start Test 6

3. High Temperature and Humidity Test 7

4. Power on/off Test with Temperature 8

5. Quickly Power On/Off Test 9

Purpose:

1. Provide a formal functional demonstration of the product design reliability.
2. Identify any design discrepancies.
3. Reliability assurance of trial samples which are designed and fabricated in accordance with the customer's product specifications.
4. Conduct robustness testing on early production samples in accordance to customer's product environmental testing specification.

Scope:

This document describes the performance requirements, validation criteria, and the validation tests which focus on BFX-AT100 product.

The DUT H/W version is 04L1 and S/W revision is v15.523.6.

Second source:

Reset IC for U401 (3PEAK / TPV809S-3TR).

The summary of test items:

No.	Item	Test Condition	Q'ty	Period	Pass Criteria	Test result
1	Cold Start Test	1. Power off, and store at - 5°C for 24 hours then power on to check function. 2. Repeat test 15 times	2	2 days	1. No functional failures both before and after the test 2. No performance degradation after the functional test 3. No visual damage to the products after inspection, such as peeling, discoloration, etc.	PASS
2	Hot Start Test	1. Power off, and store at 50°C for 24 hours then power on to check function. 2. Repeat test 15 times	2	2 days	1. No functional failures both before and after the test 2. No performance degradation after the functional test 3. No visual damage to the products after inspection, such as peeling, discoloration, etc.	PASS
3	High Temperature & Humidity Test	Power on, Operation Ta = 50°C, Humi. = 90%R.H. for 72 hours	2	3 days	1. No functional failures both during and after the test 2. No performance degradation during the functional test 3. No visual damage to the products after inspection, such as peeling, discoloration, etc.	PASS
4	Power On/Off Test with Temperature	1. Power on: 50 sec; off: 10 sec. 2. Temperature: - 5°C and 50°C 3. Cycle: 2,500 cycles per test condition 4. Total 5,000 cycles	2	6 days	1. No functional failures both during and after the test 2. No ping failures both during the test and after the test. 3. No performance degradation during the functional test 4. No visual damage to the products after inspection, such as peeling, discoloration, etc.	PASS
5	Quickly Power On/Off Test	1. Power on: 50 sec 2. Power off < 3 sec 3. Temperature: 25°C 4. Cycle: 100 cycles	4	2 days	1. No functional failures both during and after the test 2. No ping failures both during the test and after the test. 3. No performance degradation during the functional test 4. No visual damage to the products after inspection, such as peeling, discoloration, etc.	PASS

Panel Drawing:

Front




Rear



Adapter



Test setup and function test:



1. Cold Start Test


Purpose:

To demonstrate that the product can be stored at low temperature environment.

Quantity: 2 units.

Test Objective: Power off, and store at - 5°C for 24 hours the power on to check function.
Repeat test 15 times.

Test Profile:



Test Procedure:


1. Start test at 28°C and power on active full function for 1 hour.
2. Turn off the power and decrease the temperature to - 5°C and hold for 24 hours.
3. Power on the measure the DUT function for 10 min.
4. Repeat 15 times cold start test.

Pass Criteria:

1. No functional failures both before and after the test.
2. No performance degradation after the functional test.
3. No visual damage to the products after inspection, such as peeling, discoloration, etc.

Basis for Profile: IEC 60068-2-01

Test Result: **PASS**



2. Hot Start Test


Purpose:

To demonstrate that the product can be stored at high temperature environment.

Quantity: 2 units.

Test Objective: Power off, and store at 50°C for 24 hours then power on to check function.
Repeat test 15 times.

Test Profile:



Test Procedure:

1. Start test at 28°C and power on active full function for 1 hour.
2. Turn off the power and decrease the temperature to 50°C and hold for 24 hours.
3. Power on the measure the DUT function for 10 min.
4. Repeat 15 times cold start test.

Pass Criteria:

1. No functional failures both before and after the test.
2. No performance degradation after the functional test.
3. No visual damage to the products after inspection, such as peeling, discoloration, etc.

Basis for Profile: IEC 60068-2-02

Test Result: **PASS**



3. High Temperature and Humidity Test


Purpose:

To demonstrate that products can withstand the high limit temperature and the high limit humidity of an operating environment.

Quantity: 2 units.

Test Objective: Operating Temperature and Humidity: Temp. + 50°C and RH 90%, Duration: 3 days.

Test Profile:



Test Procedure:

1. Power off.
2. Start test at 25°C and RH 50%.
3. Ramp the temperature to 50°C and RH 90% in 25 minutes, then hold for 1 hour.
4. Power on the test units.
5. Hold 50°C, RH 90% for 72 hours.

Pass Criteria:

1. No functional failures both during and after the test.
2. No performance degradation during the functional test.
3. No visual damage to the products after inspection, such as peeling, discoloration, etc.

Basis for Profile: MIL-STD-202F Method 103B

Test Result: **PASS**



4. Power on/off Test with Temperature


Purpose:

The purpose of this specification is to define the power on / off test. This test is to assure the product will meet customer's specification.

Quantity: 2 units.

Test Objective:

1. Power on: 50 sec. (follow product characteristic).
2. Power off: 10 sec. (follow product characteristic).
3. Temperature: - 5°C and 50°C.
4. Cycle: 2,500 cycles per test condition.
5. Total 5,000 cycles.

Test Profile:**Test Procedure:**

1. Base on test setup and function test to check DUT function then put the DUT into chamber.
2. Temperature: - 5°C and 50°C.
3. Control the power on/off frequency, temperature and input voltage as below.
Power on/off frequency: Power on: 50 seconds/ Power off: 10 seconds.
4. Cycle: 2,500 cycles per test condition, Total: 5,000 cycles

Pass Criteria:

1. No functional failures both during and after the test.
2. No ping failures both during the test and after the test.
3. No performance degradation during the functional test
4. No visual damage to the products after inspection, such as peeling, discoloration, etc.

Test Result: **PASS**



5. Quickly Power On/Off Test

Purpose:

The purpose of this specification is to define the power on / off test. This test is to assure the product will meet customer's specification.

Quantity: 4 units.

Test Objective: 1. Base on test setup and function test to check DUT function.


2. Power off: 50 sec.

3. Power off < 3 sec.

4. Temperature: 25°C

5. Cycle: 100 cycles test condition.

Test Profile:



Test Procedure:

1. Base on test setup and function test to check DUT function.

2. Temperature: 25°C.

3. Control the power on/off frequency, temperature and input voltage as below.

Power on/off frequency: Power on: 50 seconds/ Power off < 3 seconds.

4. Total: 100 cycles.

Pass Criteria:

1. No functional failures both during and after the test.

2. No ping failures both during the test and after the test.

3. No performance degradation during the functional test

4. No visual damage to the products after inspection, such as peeling, discoloration, etc.

Test Result: **PASS**

